

Volt-Finger Detector / Driver



CE

LVD-18

The Volt-Finger Detector/Driver is intended to check for the presence of AC Voltage, signaling the user with an intermittent tone and a flashing LED.

This instrument allows the user to do both of the direct contact voltage detection and the non-contact voltage detection.

FEATURES

- Bright LED and audible alarm sound when voltage is present.
- Designed for both contact and non-contact voltage detection.
- Direct contact voltage detection: 50V~600Vac.
- Non-contact voltage detection: 50V~600Vac.
- Can be used to detect voltage in lighting fixtures, circuit breakers.
- Compact and handy.
- Can be used to find a break in a wire.
- Continuity test and basic driver function.
- Flashlight.

SPECIFICATIONS

Direct contact voltage detection	50V~600Vac
Non-contact voltage detection	50V~600Vac
Frequency	50~500Hz
Measurement category	CAT III 600V
Indication	LED and Tone
Operating conditions	Temperature : 0~40°C
	Humidity : Less than 80% R.H.
	Altitude : 2000m maximum
Power source	1.5V (AAA) × 2
Dimension	165 (L) x 27 (W) x 22 (D) mm
Weight (batteries included)	Approx. 46g
Safety standard	EN 61010-1 CAT III 600V
	EN 61326-1

